



# **Wireless – N Router/AP**

## **User's Manual**

**Model # AWR-RT-11N2**

### ***FCC Warning***

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communication. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which
- Consult the dealer or an experienced radio/TV technician for help. The receiver is connected.

***FCC Caution:*** Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate this equipment.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

### ***IMPORTANT NOTE:***

FCC Radiation Exposure Statement:

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with a minimum distance of about eight inches (20cm) between the radiator and your body.

This transmitter must not be co-located or operated in conjunction with any other antenna or transmitter. IEEE802.11b or 802.11g operation of this product in the USA is firmware-limited to channels 1 through 11.

### ***Notice***

Changes or modifications to the equipment, which are not approved by the party responsible for compliance could affect the user's authority to operate the equipment. Company has an on-going policy of upgrading its products and it may be possible that information in this document is not up-to-date.

Please check with your local distributors for the latest information.

***Copyright***

2009 All Rights Reserved.

No part of this document can be copied or reproduced in any form without written consent from the company.

***Trademarks:***

**All trade names and trademarks are the properties of their respective companies.**

***Revision History***

Revision	History
V1	1st Release


## Table of Contents

<b>1. Introduction .....</b>	<b>5</b>
<b>1.1 Features.....</b>	<b>5</b>
<b>1.2 Package Contents .....</b>	<b>5</b>
<b>1.3 LEDs Indication &amp; Connectors of Wireless Router .....</b>	<b>6</b>
<b>1.4 System Requirements.....</b>	<b>6</b>
<b>1.5 Installation Instruction .....</b>	<b>7</b>
<b>2. PC Configuration.....</b>	<b>7</b>
<b>2.1 TCP/IP Networking Setup.....</b>	<b>7</b>
<b>2.2 Setting up Internet Access .....</b>	<b>15</b>
<b>2.3 Configure Wireless Station.....</b>	<b>16</b>
<b>3. Setup Wireless Router Configurations via Web Browser.....</b>	<b>17</b>
<b>3.1 Start your Web Browser.....</b>	<b>17</b>
<b>3.2 Setup Wizard.....</b>	<b>18</b>
<b>3.2.1 Gateway .....</b>	<b>18</b>
<b>3.2.2 Bridge.....</b>	<b>21</b>
<b>3.2.3 Wireless ISP .....</b>	<b>24</b>
<b>3.3 Operation Mode .....</b>	<b>27</b>
<b>3.4 Wireless.....</b>	<b>28</b>
<b>3.4.1 Basic Settings .....</b>	<b>28</b>
<b>3.4.2 Advanced Settings.....</b>	<b>29</b>
<b>3.4.3 Security.....</b>	<b>29</b>
<b>3.4.4 Access Control.....</b>	<b>30</b>
<b>3.4.5 WDS Settings .....</b>	<b>30</b>
<b>3.4.6 Site Survey .....</b>	<b>31</b>
<b>3.4.7 WPS.....</b>	<b>31</b>
<b>3.5 TCP/IP Settings.....</b>	<b>34</b>
<b>3.5.1 LAN Interface.....</b>	<b>34</b>
<b>3.5.2 WAN Interface .....</b>	<b>35</b>
<b>3.6 Firewall .....</b>	<b>36</b>
<b>3.6.1 Port Filtering.....</b>	<b>36</b>
<b>3.6.2 IP Filtering .....</b>	<b>36</b>
<b>3.6.3 MAC Filtering.....</b>	<b>37</b>
<b>3.6.4 Port Forwarding .....</b>	<b>37</b>
<b>3.6.5 URL Filtering .....</b>	<b>38</b>
<b>3.6.6 DMZ .....</b>	<b>38</b>
<b>3.6.7 QoS.....</b>	<b>39</b>
<b>3.7 Management.....</b>	<b>40</b>
<b>3.7.1 Status .....</b>	<b>40</b>

3.7.2 Statistics .....	41
3.7.3 DDNS.....	42
3.7.4 Time Zone Setting.....	42
3.7.5 Log .....	43
3.7.6 Upgrade Firmware.....	43
3.7.7 Save/Reload Setting.....	44
3.7.8 Password .....	44
3.8 Logout .....	45
4. Troubleshooting.....	46

## 1. Introduction

This Wireless Broadband Router is a draft 802.11n compliant device that provide faster and farther range than 802.11g while backward compatible with 802.11g and 802.11b devices. This Router uses advanced broadband router chipset and wireless LAN chipset solution let you enjoy high-speed Wired and Wireless connection. Simply connect this device to a Cable or DSL modem and then you can share your high-speed Internet access with multiple PCs at your home. It creates a secure Wired and Wireless network for you to share photos, files, video, music, printer and network storage. This device also supports the latest wireless security features such as WEP, WPA, WPA2 and WPS to prevent from unauthorized access.



### 1.1 Features

- Compliant with IEEE 802.11n draft 2.0 standard
- Backward compatible with IEEE 802.11b/g
- Supports NAT, NAPT, DHCP Server/Client
- Supports VPN pass through - IPSec, PPTP, L2TP
- Supports Virtual Server / Port Trigger / Port Forward
- Supports Virtual DMZ Host, DNS Proxy, DDNS, UPnP
- Supports 64/128-bit WEP Data Encryption
- Supports WPA / WPA2 / WPS / 802.1x Authentication
- Supports WDS (Wireless Distribution System) mode
- Supports Quality of Service (QoS)
- Supports MAC Filter, Client Filter, URL/IP Filter
- Supports Hacker Pattern Detection
- Supports Auto-crossover (MDI/MID-X) function
- Supports software upgrade through Web
- Friendly web-based GUI Configuration and Management

### 1.2 Package Contents

- One Wireless 11n AP Router
- One 12V AC Power Adapter
- One CD including user's manual
- One RJ-45 Ethernet Cable


## 1.3 LEDs Indication & Connectors of Wireless Router

### Front Panel LEDs Indication



LED	Light Status	Description
PWR	On	Wireless Router is powered on.
	Off	No power.
LAN (1, 2, 3, 4)	On	LAN port is successfully connected.
	Flashing	Data is being sent or received.
WAN	On	WAN port is successfully connected
	Flashing	Data is being sent or received.
ACT (WLAN)	Flashing	Data is being sent or received.
LINK (WLAN)	On	Wireless connection is ready.

### Back Panel Connectors



Button/port	Description
Reset	Reset configurations to default. You would use the reset button only when a program error has caused your 11n AP router to hang. Press the button and hold for 10 seconds.
WPS	Click WPS button about 2-3 seconds while your are connecting a PC of wireless adapter with WPS function (you must enable WPS' PBC function).
LAN (1x, 2x, 3x, 4x)	Ethernet RJ-45 Connector connects to PC with RJ-45 Ethernet Cable.
WAN	Ethernet RJ-45 Connector connects to WAN access device, such as the Cable modem or ADSL modem.
PWR	Power connector, Connect to the power adapter packaged with the AP router.

## 1.4 System Requirements

- One or more PCs (desktop or notebook) with Ethernet interface.
- TCP/IP protocol must be installed on all PCs.

- Have valid Internet Access account and a DSL or cable modem.
- 10/100BaseT network cables with RJ-45 connectors.
- In case to use Wireless Access Point, all Wireless devices must be compliant with IEEE 802.11b/g/n.
- System with MS Internet Explorer ver. 5.0 or later, or Netscape Navigator ver. 4.7 or later.

## 1.5 Installation Instruction

- 1) Power off Wireless Router and DSL/cable modem.
- 2) Connect systems to the LAN ports on the Wireless Router with straight LAN cables.
- 3) Connect the DSL or cable modem to the WAN port on the Wireless Router.
- 4) Power on DSL or cable modem first, then connect power adapter to the power jack on the Wireless Router and plug the power cable into an outlet.
- 5) Check LEDs.
  - a) Once power on Wireless Router, Power LED should be on.
  - b) LAN LED should be on for each active LAN connection.
  - c) The WAN LED should be on when the DSL or cable modem is connected.

**Warning:** Only use the power adapter is provided from this package, use other power adapter may cause hardware damage

## 2. PC Configuration


User needs to configure TCP/IP network settings, Internet access configuration and Wireless configuration for each system within Wireless Router's LAN network.

By default, Wireless Router acts as a DHCP server for server version of Windows, it automatically assigns IP address to each system when systems boot up. For all non-server versions of Windows, the default TCP/IP setting acts as a DHCP client. If user chooses fixed IP addresses for client systems, the **Gateway** of the client system must be set to the IP address of the Wireless Router and **DNS** of the client system should be set to the address provided by your ISP.


### 2.1 TCP/IP Networking Setup

#### Checking TCP/IP Settings for Windows 9x/Me


- a) Select "**Start → Control Panel → Network**", the window below will appear:




b) Click **“Properties”**, the window below will appear:



- If you decide to use DHCP, select “**Obtain an IP address automatically**”, then click “OK” to confirm your settings. Once you restart your system, Wireless Router will obtain an IP address for this system.
  - If you decide to use fixed IP address for your system, select “**Specify an IP address**”, and make sure that **IP Address** and **Subnet Mask** are correct.
- c) Select “**Gateway**” tab and enter correct gateway address in “**New gateway**” field, then click “**Add**”:




- d) Select “**DNS Configuration**” tab and make sure select “**Enable DNS**”, enter the DNS address provides from your ISP in the “**DNS Server Search Order**” field, then click “**Add**”:




#### Checking TC/IP Setting for Windows NT4.0


- a) Select “**Control Panel → Network**”, click “**Protocols**” tab then select “**TCP/IP protocol**”, window shown as below will appear:



- b) Click **“Properties”**, window shown as below will appear.




- Select the network card on your system from **“Adapter”** field.
  - If you decide to use IP address from Wireless Router, select **“Obtain an IP address from a DHCP server”**.
  - If you decide to use the IP address you are desired, select **“Specify an IP address”**. Make sure enter correct addresses in **“IP Address”** and **“Subnet Mask”** fields.
  - You must set Wireless Router’s IP address as **“Default Gateway”**.
- c) To enter DNS address is provided from your ISP. Select **“DNS”** tab, click **“Add”** under **“DNS Service Search Order”** list, then enter DNS Server IP address in **“TCP/IP DNS Server”** window and click **“Add”**.




### Checking TCP/IP Settings for Windows 2000

- a) Select **"Start → Control Panel → Network and Dial-up Connection"** and right click **"Local Area Connection"** then click **"Properties"**:




- b) Select the “**Internet Protocol (TCP/IP)**” for the network card on your system, then click “**Properties**”, window shown as below will appear.




- If you decide to use IP address from Wireless Router, select “**Obtain an IP address automatically**”.
- If you decide to use the IP address you are desired, select “**Use the following IP address**”. Make sure enter correct addresses in “**IP Address**” and “**Subnet Mask**” fields.
- You must set Wireless Router’s IP address as “**Default Gateway**”.
- If the DNS Server fields are empty, select “**Use the following DNS server addresses**” and enter the DNS address is provided by your ISP, then click “**OK**”.

#### **Checking TCP/IP Settings for Windows XP**

- a) Click “**Start**”, select “**Control Panel → Network Connection**” and right click “**Local Area Connection**” then select “**Properties**”. The window shown as below will appear.



- b) Select “**Internet Protocol (TCP/IP)**” then click “**Properties**”, window shown as below will appear.



- If you decide to use IP address from Wireless Router, select **“Obtain an IP address automatically”**.
- If you decide to use the IP address you are desired, select **“Use the following IP address”**. Make sure enter correct addresses in **“IP Address”** and **“Subnet Mask”** fields.
- You must set Wireless Router’s IP address as **“Default Gateway”**.
- If the DNS Server fields are empty, select **“Use the following DNS server addresses”** and enter the DNS address is provided by your ISP, then click **“OK”**.

## 2.2 Setting up Internet Access

This section describes how to setup Wireless Router Internet access through DSL or cable modem.

### For Windows OS

To access Internet via wireless router with **Static IP** method as example, the set up procedures are showing below:

- a) Access your ADSL Router Modem and configure the Internet setup (VPI, VCI, and Encapsulation); and then, save the settings. *(PS. Most of ISP companies will set the default internet setup already for the user).*
- b) Log in your wireless broadband router, Select **“TCP/IP Setting”** Section → **“WAN Interface”** → Choose **“Static IP”**.
- c) Enter **“IP Address”**, **“Subnet Mask”** and **“Server IP Address”**
- d) In the below **“DNS”** option, select **“Set DNS Manually”** and enter the **DNS Address** which is provided by your ISP; and then click **“Apply Changes”** button to save the settings.
- e) You can back to **“Management”** section → **“Status”** to check the Internet status.

### For Macintosh Clients

To access Internet via wireless router on Macintosh system, the set up procedures are showing below:

- a) Open the TCP/IP Control Panel.
- b) Select **Ethernet** from the Connect via pop-up menu.
- c) Select **Using DHCP Server** from the Configure pop-up menu. The **DHCP Client ID** field can be left blank.
- d) Close the TCP/IP panel and save your new settings.

If you decide to assign IP addresses manually instead of DHCP, set the **Router Address** field with wireless router’s IP address and make sure DNS settings are correct.

### For Linux Clients

To access Internet via the wireless router, you need to set the wireless router as the “Gateway”. Make sure login as “root” before attempting any changes.

#### Fixed IP Address

Most Linux installations use fixed IP address, if you wish to use a fixed IP address, make sure make the following changes.

- a) Set “**Default Gateway**” with the IP address of the wireless router.
- b) Make sure DNS settings are correct.

To act as a DHCP Client (recommended)

The procedures below may vary depending on version of Linux and X-windows shell.

- a) Start X-Windows.
- b) Select **Control Panel → Network**.
- c) Select the “**Interface**” entry for your Network card. Normally, this is called “**eth0**”.
- d) Click “**Edit**” button, set the “**protocol**” to “**DHCP**” and save.
- e) To apply all changes, use **Deactivate** and **Activate** buttons, if it is possible, restart your system.

## 2.3 Configure Wireless Station

This section describes how to configure all the wireless stations use Wireless Router as an Access Point. Each wireless station must have compatible settings as below.

Mode	All wireless stations must be set to “Infrastructure” mode.
SSID (ESSID)	This code must match the value uses for the Wireless Router. (Note: SSID code is case sensitive.)
WEP	By default, WEP encryption is set to 64-bits 10 hex digit.
WPA	By default, WPA-PSK Pass Phrase is set at PassPhrase, WPA G-Rekey Interval is set at 0 and WPA Data Encryption is at TKIP.

### 3. Setup Wireless Router Configurations via Web Browser

The Wireless Router comes with a web-based configuration utility. Users can access this configuration utility from any of client system within Wireless Router's LAN. For best results, either use Microsoft Internet Explorer 5.0 or later, or Netscape Navigator 4.7 or later.

Before you start configuring your Wireless Router, you have to get following information from your ISP:

- a) Has your ISP assigned you a static IP address, or they will assign one to you dynamically? If you have received a static IP address, what is it?
- b) Does your ISP use PPPoE? If so, what is your PPPoE username and password?

If you are not sure of above questions, please contact your ISP.

#### 3.1 Start your Web Browser

To use the Web-Based Utility, you have to launch your Internet Browser (MS IE 5.0 or later, Netscape Navigator 4.7 or later).

**Step1:** Enter Wireless Router default IP address <http://192.168.1.1> in the Address field then hit Enter key:




**Step2:** Login dialog box will appear, enter **admin** as User Name and default password is **1234**, then click "OK" to login web-based utility.



## 3.2 Setup Wizard

This Setup Wizard will guide you to configure access for the first time. Please follow the setup wizard step by step.



Depend on different modes, the setup wizard will be different. Please follow the below brief descriptions:

### 3.2.1 Gateway

**(1) Setup Operation Mode – Gateway:** In this mode, the device is supposed to connect to internet via ADSL/Cable Modem. The NAT is enabled and PCs in four LAN ports share the same IP to ISP through WAN port. The connection type can be setup in WAN port. The connection type can be setup in WAN page by using PPPoE, DHCP client, PPTP client, L2TP client or static IP.

**WLAN Access Point**

**1. Operation Mode**

You can setup different modes to LAN and WLAN interface for NAT and bridging function.

- Gateway:** In this mode, the device is supposed to connect to internet via ADSL/Cable Modem. The NAT is enabled and PCs in four LAN ports share the same IP to ISP through WAN port. The connection type can be setup in WAN page by using PPPOE, DHCP client, PPTP client, L2TP client or static IP.
- Bridge:** In this mode, all ethernet ports and wireless interface are bridged together and NAT function is disabled. All the WAN related function and firewall are not supported.
- Wireless ISP:** In this mode, all ethernet ports are bridged together and the wireless client will connect to ISP access point. The NAT is enabled and PCs in ethernet ports share the same IP to ISP through wireless LAN. You must set the wireless to client mode first and connect to the ISP AP in Site-Survey page. The connection type can be setup in WAN page by using PPPOE, DHCP client, PPTP client, L2TP client or static IP.

Cancel <<Back Next>>

**(2) Choose your Time Zone:** You can maintain the system time by synchronizing with a public server over the Internet.

**WLAN Access Point**

**2. Time Zone Setting**

You can maintain the system time by synchronizing with a public time server over the Internet.


- Enable NTP client update**
- Automatically Adjust Daylight Saving**

**Time Zone Select :** (GMT+08:00)Taipei


**NTP server :** 192.5.41.41 - North America

Cancel <<Back Next>>


**(3) Setup LAN Interface:** This page is used to configure the parameters for local area network which connects to the LAN port of your AP Router. Here you may change the setting for IP address, subnet mask, DHCP, etc.




**(4) Setup WAN Interface:** This page is used to configure the parameters for Internet network which connects to the WAN port of your AP Router. Here you may change the access method to static IP, DHCP, PPPoE, PPTP, or L2TP by click the item value of WAN Access type.



**(5) Wireless LAN Setting:** This page is used to configure the parameters for wireless LAN clients who may connect to your AP Router.



**(6) Wireless Security:** This page allows you setup the wireless security. Turn on WEP or WPA by using Encryption Keys could prevent any unauthorized access to your wireless network.



### 3.2.2 Bridge

**(1) Setup Operation Mode – Bridge:** In this mode, all Ethernet ports and wireless interface are bridged together and NAT function is disabled. All the WAN related function and firewall are not supported.

**WLAN Access Point**

**1. Operation Mode**

You can setup different modes to LAN and WLAN interface for NAT and bridging function.

- Gateway:** In this mode, the device is supposed to connect to internet via ADSL/Cable Modem. The NAT is enabled and PCs in four LAN ports share the same IP to ISP through WAN port. The connection type can be setup in WAN page by using PPPOE, DHCP client, PPTP client, L2TP client or static IP.
- Bridge:** In this mode, all ethernet ports and wireless interface are bridged together and NAT function is disabled. All the WAN related function and firewall are not supported.
- Wireless ISP:** In this mode, all ethernet ports are bridged together and the wireless client will connect to ISP access point. The NAT is enabled and PCs in ethernet ports share the same IP to ISP through wireless LAN. You must set the wireless to client mode first and connect to the ISP AP in Site-Survey page. The connection type can be setup in WAN page by using PPPOE, DHCP client, PPTP client, L2TP client or static IP.

Cancel <<Back Next>>

**(2) Choose your Time Zone:** You can maintain the system time by synchronizing with a public server over the Internet.

**WLAN Access Point**

**2. Time Zone Setting**

You can maintain the system time by synchronizing with a public time server over the Internet.

- Enable NTP client update**
- Automatically Adjust Daylight Saving**

**Time Zone Select :** (GMT+08:00)Taipei

**NTP server :** 192.5.41.41 - North America

Cancel <<Back Next>>

**(3) Setup LAN Interface:** This page is used to configure the parameters for local area network which connects to the LAN port of your AP Router. Here you may change the setting for IP address, subnet mask, DHCP, etc.

**WLAN Access Point**

Site contents:  
 Setup Wizard  
 Operation Mode  
 Wireless  
 TCP/IP Settings  
 Firewall  
 QoS  
 Management  
 Logout

### 3. LAN Interface Setup

This page is used to configure the parameters for local area network which connects to the LAN port of your Access Point. Here you may change the setting for IP addresss, subnet mask, DHCP, etc..

IP Address:

Subnet Mask:

**Attention:** DHCP server of LAN will be disabled when you are using BRIDGE mode. Please remember the IP address in this page and set up your computer with another fix IP in the same domain to connect to this setup page in the future.

**For Example:** If the IP address of LAN is 192.168.1.1 and the Netmask is 255.255.255.0, you can setup your computer with fixed IP 192.168.1.2 and Netmask as 255.255.255.0. After that, you can type <http://192.168.1.1> in the web browser to connect this setup page.

**(4) Wireless Basic Settings:** This page is used to configure the parameters for wireless LAN clients who may connect to your AP Router.

**WLAN Access Point**

Site contents:  
 Setup Wizard  
 Operation Mode  
 Wireless  
 TCP/IP Settings  
 Firewall  
 QoS  
 Management  
 Logout

### 5. Wireless Basic Settings

This page is used to configure the parameters for wireless LAN clients which may connect to your Access Point.

Band:

Mode:

Network Type:

SSID:

Channel Width:

ControlSideband:

Channel Number:

Enable Mac Clone (Single Ethernet Client)

**(5) Wireless Security:** This page allows you setup the wireless security. Turn on WEP or WPA by using Encryption Keys could prevent any unauthorized access to your wireless network.


The screenshot shows the 'WLAN Access Point' configuration interface. On the left is a 'Site contents' sidebar with a tree view containing: Setup Wizard, Operation Mode, Wireless, TCP/IP Settings, Firewall, QoS, Management, and Logout. The main content area is titled '6. Wireless Security Setup'. Below the title is a descriptive paragraph: 'This page allows you setup the wireless security. Turn on WEP or WPA by using Encryption Keys could prevent any unauthorized access to your wireless network.' Below this is an 'Encryption:' label followed by a dropdown menu. The dropdown menu is open, showing options: None, WEP, WPA (TKIP), WPA2(AES), and WPA2 Mixed. At the bottom right of the main area are three buttons: 'Cancel', '<<Back', and 'Finished'.

### 3.2.3 Wireless ISP

**(1) Setup Operation Mode – Wireless ISP:** In this mode, all Ethernet ports are bridged together and the wireless client will connect to ISP access point. The NAT is enabled and PCs in Ethernet ports share the same IP to ISP through wireless LAN. You must set the wireless to client mode first and connect to the ISP AP in Site-Survey page. The connection type can be setup in WAN page by using PPPoE, DHCP client, PPTP client, L2TP client or static IP.

The screenshot shows the 'WLAN Access Point' configuration interface. On the left is a 'Site contents' sidebar with a tree view containing: Setup Wizard, Operation Mode, Wireless, TCP/IP Settings, Firewall, QoS, Management, and Logout. The main content area is titled '1. Operation Mode'. Below the title is a descriptive paragraph: 'You can setup different modes to LAN and WLAN interface for NAT and bridging function.' Below this are three radio button options: 'Gateway', 'Bridge', and 'Wireless ISP'. The 'Wireless ISP' option is selected. Each option has a detailed description of its functionality. At the bottom right of the main area are three buttons: 'Cancel', '<<Back', and 'Next>>'.


**(2) Choose your Time Zone:** You can maintain the system time by synchronizing with a public server over the Internet.



The screenshot shows the 'WLAN Access Point' configuration interface. On the left is a navigation menu with 'Site contents' including Setup Wizard, Operation Mode, Wireless, TCP/IP Settings, Firewall, QoS, Management, and Logout. The main content area is titled '2. Time Zone Setting'. It contains the following elements:

- A header bar with the text 'WLAN Access Point' and a small box containing '請先登入以存取您的 Google 書籤'.
- A sub-header '2. Time Zone Setting'.
- A descriptive text: 'You can maintain the system time by synchronizing with a public time server over the Internet.'
- Two checkboxes:  'Enable NTP client update' and  'Automatically Adjust Daylight Saving'.
- A 'Time Zone Select' dropdown menu with '(GMT+08:00)Taipei' selected.
- An 'NTP server' dropdown menu with '192.5.41.41 - North America' selected.
- Three buttons at the bottom: 'Cancel', '<<Back', and 'Next>>'.

**(3) Setup LAN Interface:** This page is used to configure the parameters for local area network which connects to the LAN port of your AP Router. Here you may change the setting for IP address, subnet mask, DHCP, etc.



The screenshot shows the 'WLAN Access Point' configuration interface. On the left is a navigation menu with 'Site contents' including Setup Wizard, Operation Mode (highlighted in red), Wireless, TCP/IP Settings, Firewall, QoS, Management, and Logout. The main content area is titled '3. LAN Interface Setup'. It contains the following elements:

- A header bar with the text 'WLAN Access Point'.
- A sub-header '3. LAN Interface Setup'.
- A descriptive text: 'This page is used to configure the parameters for local area network which connects to the LAN port of your Access Point. Here you may change the setting for IP address, subnet mask, DHCP, etc..'
- An 'IP Address' input field containing '192.168.1.1'.
- A 'Subnet Mask' input field containing '255.255.255.0'.
- Three buttons at the bottom: 'Cancel', '<<Back', and 'Next>>'.

**(4) Setup WAN Interface:** This page is used to configure the parameters for Internet network which connects to the WAN port of your AP Router. Here you may change the access method to static IP, DHCP, PPPoE, PPTP, or L2TP by click the item value of WAN Access type.

**WLAN Access Point**

**4. WAN Interface Setup**

This page is used to configure the parameters for Internet network which connects to the WAN port of your Access Point. Here you may change the access method to static IP, DHCP, PPPoE, PPTP or L2TP by click the item value of WAN Access type.

Site contents:  
 Setup Wizard  
 Operation Mode  
 Wireless  
 TCP/IP Settings  
 Firewall  
 QoS  
 Management  
 Logout

WAN Access Type: L2TP

IP Address: 172.1.1.2

Subnet Mask: 255.255.255.0

Server IP Address: 172.1.1.1

User Name: l2tp

Password: ●●●●

Cancel <<Back Next>>

**(5) Wireless LAN Setting:** This page is used to configure the parameters for wireless LAN clients who may connect to your AP Router.

**WLAN Access Point**

**5. Wireless Basic Settings**

This page is used to configure the parameters for wireless LAN clients which may connect to your Access Point.

Site contents:  
 Setup Wizard  
 Operation Mode  
 Wireless  
 TCP/IP Settings  
 Firewall  
 QoS  
 Management  
 Logout

Band: 2.4 GHz (B+G+N)

Mode: AP

Network Type: Infrastructure

SSID: RTL865x-GW

Channel Width: 40MHz

ControlSideband: Upper

Channel Number: 11

Enable Mac Clone (Single Ethernet Client)

Cancel <<Back Next>>

**(6) Wireless Security:** This page allows you setup the wireless security. Turn on WEP or WPA by using Encryption Keys could prevent any unauthorized access to your wireless network.

### 3.3 Operation Mode

You can setup different modes to LAN and WLAN interface for NAT and bridging function.

**Gateway:** In this mode, the device is supposed to connect to internet via ADSL/Cable Modem. The NAT is enabled and PCs in LAN ports share the same IP to ISP through WAN port. The connection type can be setup in WAN page by using PPPoE, DHCP client, PPTP client, L2TP client or static IP.

**Bridge:** In this mode, all Ethernet ports and wireless interface are bridged together and NAT function is disabled. All the WAN related function and firewall are not supported.

**Wireless ISP:** In this more, all Ethernet ports are bridged together and the wireless client will

connect to ISP AP Router. The NAT is enabled and PCs in Ethernet ports share the same IP to ISP through wireless LAN. You must set the wireless to client mode first and connect to the ISP AP in Site-Survey page. The connection type can be setup in WAN page by using PPPoE, DHCP client, L2TP client or static IP.

### 3.4 Wireless

#### 3.4.1 Basic Settings

This page is used to configure the parameters for wireless LAN clients who may connect to your AP Router. Here you may change wireless encryption settings as well as wireless network parameters.

The screenshot shows the 'WLAN Access Point' configuration interface. On the left is a navigation tree with 'Wireless' selected. The main content area is titled 'Wireless Basic Settings' and contains the following configuration options:

- Disable Wireless LAN Interface**
- Band:** 2.4 GHz (B+G+N)
- Mode:** AP (with a 'Multiple AP' button)
- Network Type:** Infrastructure
- SSID:** RTL865x-GW
- Channel Width:** 40MHz
- Control Sideband:** Upper
- Channel Number:** 11
- Broadcast SSID:** Enabled
- WMM:** Enabled
- Data Rate:** Auto
- Associated Clients:** Show Active Clients
- Enable Mac Clone (Single Ethernet Client)**
- Enable Universal Repeater Mode (Acting as AP and client simultaneously)**
- SSID of Extended Interface:** [Empty text box]

At the bottom of the configuration area are two buttons: 'Apply Changes' and 'Reset'.

### 3.4.2 Advanced Settings

These settings are only for more technically advanced users who have a sufficient knowledge about the wireless LAN. These settings should not be changed unless you know what effect the changes will have on your AP Router.

The screenshot shows the 'WLAN Access Point' configuration interface. On the left is a navigation tree with 'Advanced Settings' selected. The main content area is titled 'Wireless Advanced Settings' and contains a warning: 'These settings are only for more technically advanced users who have a sufficient knowledge about wireless LAN. These settings should not be changed unless you know what effect the changes will have on your Access Point.' Below this are several settings:

- Fragment Threshold:** 2346 (range 256-2346)
- RTS Threshold:** 2347 (range 0-2347)
- Beacon Interval:** 100 (range 20-1024 ms)
- Preamble Type:**  Long Preamble  Short Preamble
- IAPP:**  Enabled  Disabled
- Protection:**  Enabled  Disabled
- Aggregation:**  Enabled  Disabled
- Short GI:**  Enabled  Disabled
- RF Output Power:**  100%  70%  50%  35%  15%

Buttons for 'Apply Changes' and 'Reset' are located at the bottom.

### 3.4.3 Security

This page allows you setup the wireless security. Turn on WEP or WPA by using Encryption Keys could prevent any unauthorized access to your wireless network.

The screenshot shows the 'WLAN Access Point' configuration interface for 'Wireless Security Setup'. The navigation tree on the left has 'Security' selected. The main content area is titled 'Wireless Security Setup' and contains a warning: 'This page allows you setup the wireless security. Turn on WEP or WPA by using Encryption Keys could prevent any unauthorized access to your wireless network.' Below this are the following settings:

- Select SSID:** Root AP - RTL865x-GW (dropdown menu)
- Encryption:** Disable (dropdown menu)
- 802.1x Authentication:**

Buttons for 'Apply Changes' and 'Reset' are located at the top right.

### 3.4.4 Access Control

If you choose “Allowed Listed”, only those clients whose wireless MAC addresses are in the access control list will be able to connect to your AP Router. When “Deny Listed” is selected, these wireless clients on the list will not be able to connect the AP Router.

The screenshot shows the 'WLAN Access Point' configuration interface. On the left is a navigation tree with 'Wireless' expanded to 'Access Control'. The main content area is titled 'Wireless Access Control' and contains the following elements:

- A descriptive paragraph: "If you choose 'Allowed Listed', only those clients whose wireless MAC addresses are in the access control list will be able to connect to your Access Point. When 'Deny Listed' is selected, these wireless clients on the list will not be able to connect the Access Point."
- 'Wireless Access Control Mode': A dropdown menu currently set to 'Disable'.
- 'MAC Address' and 'Comment' input fields.
- 'Apply Changes' and 'Reset' buttons.
- 'Current Access Control List': A table with columns 'MAC Address', 'Comment', and 'Select'. Below the table are 'Delete Selected', 'Delete All', and 'Reset' buttons.

### 3.4.5 WDS Settings

Wireless Distribution System uses wireless media to communicate with other APs, like the Ethernet does. To do this, you must set these APs in the same channel and set MAC address of other APs which you want to communicate with in the table and enable the WDS.

The screenshot shows the 'WLAN Access Point' configuration interface. On the left is a navigation tree with 'Wireless' expanded to 'WDS settings'. The main content area is titled 'WDS Settings' and contains the following elements:

- A descriptive paragraph: "Wireless Distribution System uses wireless media to communicate with other APs, like the Ethernet does. To do this, you must set these APs in the same channel and set MAC address of other APs which you want to communicate with in the table and then enable the WDS."
- 'Enable WDS': An unchecked checkbox.
- 'MAC Address' input field.
- 'Data Rate': A dropdown menu currently set to 'Auto'.
- 'Comment' input field.
- 'Apply Changes', 'Reset', 'Set Security', and 'Show Statistics' buttons.
- 'Current WDS AP List': A table with columns 'MAC Address', 'Tx Rate (Mbps)', 'Comment', and 'Select'. Below the table are 'Delete Selected', 'Delete All', and 'Reset' buttons.

### 3.4.6 Site Survey

This page provides tool to scan the wireless network. If any AP Router or IBSS is found, you could choose to connect it manually when client mode is enabled.

The screenshot shows the 'WLAN Access Point' configuration interface. On the left is a navigation menu with 'Wireless' selected. The main content area is titled 'Wireless Site Survey' and contains a table of detected wireless networks. Below the table are 'Refresh' and 'Connect' buttons.

SSID	BSSID	Channel	Type	Encrypt	Signal
default	00:06:4f:34:9b:8e	3 (B+G)	AP	no	23
WR514VN_FTP_Server	00:0c:43:28:80:00	8 (B+G+N)	AP	WPA-PSK/WPA2-PSK	15

### 3.4.7 WPS

This page allows you to change the setting for WPS (Wi-Fi Protected Setup). Using this feature could let your wireless client automatically synchronize its setting and connect to the Access Point in a minute without any hassle.

The screenshot shows the 'WLAN Access Point' configuration interface for 'Wi-Fi Protected Setup'. The left navigation menu has 'WPS' selected. The main content area is titled 'Wi-Fi Protected Setup' and contains configuration options for WPS, including a 'Disable WPS' checkbox, 'WPS Status' (Configured/UnConfigured), 'Self-PIN Number' (80484080), 'Push Button Configuration' (Start PBC), and 'Client PIN Number' (Start PIN).

Wi-Fi Protected Setup was designed to ease setup of security enabled WiFi networks in the home and small office environment. It supports methods that are familiar to most consumers to configure a network and enable security, like pushing a button (PBC method) or entering a PIN


code (PIN method). The new system, which will be incorporated in Windows Vista, will work with computers, gateways peripherals, and consumer electronics.

You would initiate a WPS mode on gateway and then enter a simple sequence of digits (like a PIN code) or press a button, use a similarly easy method to start a secure key exchange to retrieve the WPA/WPA2 key.

This function allows you to change the setting for WPS (Wi-Fi Protected Setup). WPS can help your wireless client earlier automatically connect to the Access Point.


### AP Operation

In Realtek AP web server, you could find an WPS web page shown as the figure below:




(Figure 1)

To use WPS, you only need to click the button of "Start PBC". Then click "OK".




## Windows Utility Operation (for RTL8192U Adapter)

Launch Realtek wireless client utility on Windows platform (2K or XP), you will see there is an Wi-Fi Protect Setup tab existed, click the tab you will see a interface as shown in following figure:




(Figure 2)

Push the “PBC(Push Button Config)” in this page, WPS feature will automatically setup the setting.



(Figure 3)

After push “**Push Button Config (PBC)**” button, the program will automatically connect to the AP router which has the feature of RTLTEK WPS. When connection is successful, you will see the screen as below:




(Figure 4)

## 3.5 TCP/IP Settings

### 3.5.1 LAN Interface

This page is used to configure the parameters for local area network which connects to the LAN port of your AP Router. Here you may change the setting for IP addresses, subnet mask, DHCP...etc.



### 3.5.2 WAN Interface

This page is used to configure the parameters for Internet network which connects to the WAN port of your AP Router. Here you may change the Access Method to static IP, PPPoE, PPTP or L2TP by click the item value of WAN Access Type.

## WLAN Access Point

Site contents:

- Setup Wizard
- Operation Mode
- Wireless
- TCP/IP Settings
- LAN Interface
- WAN Interface
- Firewall
- QoS
- Management
- Logout

**WAN Access Type:**

**IP Mode :**

**IP Address:**

**Subnet Mask:**

**Default Gateway:**

**Server IP Address:**

**User Name:**

**Password:**

**MTU Size:**  (1400-1460 bytes)

**Attain DNS Automatically**

**Set DNS Manually**

**DNS 1:**

**DNS 2:**

**DNS 3:**

**Clone MAC Address:**

**Enable uPNP**

**Enable IGMP Proxy**

**Enable Ping Access on WAN**

**Enable Web Server Access on WAN**

**Access Port Number:**

**Enable IPsec pass through on VPN connection**

**Enable PPTP pass through on VPN connection**

**Enable L2TP pass through on VPN connection**

## 3.6 Firewall

### 3.6.1 Port Filtering

Entries in this table are used to restrict certain types of data packets from your local network to Internet through the Gateway. Use of such filter can be helpful securing or restricting your local network.

The screenshot shows the 'WLAN Access Point' configuration page for 'Port Filtering'. On the left is a navigation tree with 'Firewall' expanded to 'Port Filtering'. The main content area has a title 'Port Filtering' and a descriptive paragraph. Below is a form with an 'Enable Port Filtering' checkbox, 'Port Range' input fields, a 'Protocol' dropdown set to 'Both', and a 'Comment' input field. There are 'Apply Changes' and 'Reset' buttons. Below the form is a 'Current Filter Table' with a table header and three buttons: 'Delete Selected', 'Delete All', and 'Reset'.

**WLAN Access Point**

### Port Filtering

Entries in this table are used to restrict certain types of data packets from your local network to Internet through the Gateway. Use of such filters can be helpful in securing or restricting your local network.

**Enable Port Filtering**

Port Range:  -  Protocol:  Comment:

**Current Filter Table:**

Port Range	Protocol	Comment	Select
------------	----------	---------	--------

### 3.6.2 IP Filtering

Entries in this table are used to restrict certain types of data packets from your local network to Internet through the Gateway. Use of such filters can be helpful in securing or restricting your local network.

The screenshot shows the 'WLAN Access Point' configuration page for 'IP Filtering'. On the left is a navigation tree with 'Firewall' expanded to 'IP Filtering'. The main content area has a title 'IP Filtering' and a descriptive paragraph. Below is a form with an 'Enable IP Filtering' checkbox, 'Local IP Address' input field, a 'Protocol' dropdown set to 'Both', and a 'Comment' input field. There are 'Apply Changes' and 'Reset' buttons. Below the form is a 'Current Filter Table' with a table header and three buttons: 'Delete Selected', 'Delete All', and 'Reset'.

**WLAN Access Point**

### IP Filtering

Entries in this table are used to restrict certain types of data packets from your local network to Internet through the Gateway. Use of such filters can be helpful in securing or restricting your local network.

**Enable IP Filtering**

Local IP Address:  Protocol:  Comment:

**Current Filter Table:**

Local IP Address	Protocol	Comment	Select
------------------	----------	---------	--------

### 3.6.3 MAC Filtering

Entries in this table are used to restrict certain types of data packets from your local network to Internet through the Gateway. Use of such filters can be helpful in securing or restricting your local network.

The screenshot shows the 'WLAN Access Point' configuration page for 'MAC Filtering'. On the left is a navigation tree with 'MAC Filtering' selected. The main content area has a title 'MAC Filtering' and a descriptive paragraph. Below is a checkbox for 'Enable MAC Filtering', followed by input fields for 'MAC Address' and 'Comment', and 'Apply Changes' and 'Reset' buttons. A 'Current Filter Table' section contains a table with columns 'MAC Address', 'Comment', and 'Select', and buttons for 'Delete Selected', 'Delete All', and 'Reset'.

**WLAN Access Point**

### MAC Filtering

Entries in this table are used to restrict certain types of data packets from your local network to Internet through the Gateway. Use of such filters can be helpful in securing or restricting your local network.

Enable MAC Filtering

MAC Address:  Comment:

**Current Filter Table:**

MAC Address	Comment	Select
-------------	---------	--------

### 3.6.4 Port Forwarding

Entries in this table allow you to automatically redirect common network services to a specific machine behind the NAT firewall. These settings are only necessary if you wish to host some sort of server like a web server or mail server on the private local network behind your Gateway's NAT firewall.

The screenshot shows the 'WLAN Access Point' configuration page for 'Port Forwarding'. On the left is a navigation tree with 'Port Forwarding' selected. The main content area has a title 'Port Forwarding' and a descriptive paragraph. Below is a checkbox for 'Enable Port Forwarding', followed by input fields for 'IP Address', a 'Protocol' dropdown menu (set to 'Both'), 'Port Range' input fields, and a 'Comment' field, and 'Apply Changes' and 'Reset' buttons. A 'Current Port Forwarding Table' section contains a table with columns 'Local IP Address', 'Protocol', 'Port Range', 'Comment', and 'Select', and buttons for 'Delete Selected', 'Delete All', and 'Reset'.

**WLAN Access Point**

### Port Forwarding

Entries in this table allow you to automatically redirect common network services to a specific machine behind the NAT firewall. These settings are only necessary if you wish to host some sort of server like a web server or mail server on the private local network behind your Gateway's NAT firewall.

Enable Port Forwarding

IP Address:  Protocol:  Port Range:  -  Comment:

**Current Port Forwarding Table:**

Local IP Address	Protocol	Port Range	Comment	Select
------------------	----------	------------	---------	--------

### 3.6.5 URL Filtering

URL filter is used to deny LAN users from accessing the internet. Block those URLs which contain keywords listed below.

The screenshot shows the 'WLAN Access Point' configuration page for 'URL Filtering'. On the left is a navigation tree with 'URL Filtering' selected. The main content area has a title 'URL Filtering' and a descriptive paragraph: 'URL filter is used to deny LAN users from accessing the internet. Block those URLs which contain keywords listed below.' Below this is a checkbox for 'Enable URL Filtering' which is unchecked. A text input field for 'URL Address' is empty. There are 'Apply Changes' and 'Reset' buttons. Below that is a section titled 'Current Filter Table:' with a table header containing 'URL Address' and 'Select' columns. Below the table are 'Delete Selected', 'Delete All', and 'Reset' buttons.

### 3.6.6 DMZ

A Demilitarized Zone is used to provide Internet service without sacrificing unauthorized access to its local private network. Typically, the DMZ host contains devices accessible to Internet traffic, such as Web (HTTP) servers, FTP servers, SMTP(e-mail) servers and DNS servers.

The screenshot shows the 'WLAN Access Point' configuration page for 'DMZ'. On the left is a navigation tree with 'DMZ' selected. The main content area has a title 'DMZ' and a descriptive paragraph: 'A Demilitarized Zone is used to provide Internet services without sacrificing unauthorized access to its local private network. Typically, the DMZ host contains devices accessible to Internet traffic, such as Web (HTTP) servers, FTP servers, SMTP (e-mail) servers and DNS servers.' Below this is a checkbox for 'Enable DMZ' which is unchecked. A text input field for 'DMZ Host IP Address' is empty. There are 'Apply Changes' and 'Reset' buttons.

### 3.6.7 QoS

Use this section to configure Realtek's QoS. The QoS settings improve your online gaming experience by ensuring that your game traffic is prioritized over other network traffic, such as FTP or Web.

The screenshot displays the 'WLAN Access Point' configuration interface. On the left is a navigation menu with 'QoS' selected. The main content area is titled 'QoS' and contains a 'QoS SETUP' section and a '10 -- QoS RULES' section.

**QoS SETUP**

Enable QoS :

Automatic Uplink Speed :

Manual Uplink Speed : 512 kbps << Select Transmission Rate

**10 -- QoS RULES**

Name	Priority (1 is highest)	Protocol
<input type="text"/>	<input type="text"/> (1..255)	<input type="text"/> << TCP
Local IP Range	<input type="text"/> to <input type="text"/>	Local Port Range
<input type="text"/>	<input type="text"/>	<input type="text"/> to <input type="text"/>
Remote IP Range	<input type="text"/>	Remote Port Range
<input type="text"/>	<input type="text"/>	<input type="text"/> to <input type="text"/>

The 'QoS RULES' section contains ten identical rule entries, each with the same default settings: Name (empty), Priority (1), Protocol (TCP), Local IP Range (0.0.0.0 to 255.255.255.255), Remote IP Range (0.0.0.0 to 255.255.255.255), Local Port Range (0 to 65535), and Remote Port Range (0 to 65535).

How to setup your QoS:

1. In QoS Setup Section, **Enable QoS** feature.
2. Choose Uplink Speed: **“Automatic”** or **“Manual”**
3. Configure QoS Rules – Name, Priority (1~255, 1 is highest), Protocol, Local IP range, Local Port Range, Remote IP Range, and Remote Port Range.
4. Click **“Save Settings”** to save QoS configurations.

**WLAN Access Point**

**QoS**

Use this section to configure Realtek's QoS. The QoS settings improve your online gaming experience by ensuring that your game traffic is prioritized over other network traffic, such as FTP or Web.

Save Settings    Don't Save Settings

**QoS SETUP**

Enable QoS :

Automatic Uplink Speed :

Manual Uplink Speed : 512 kbps << Select Transmission Rate

**10 -- QoS RULES**

Name	Priority (1 is highest)	Protocol	Local IP Range	Local Port Range	Remote IP Range	Remote Port Range
<input checked="" type="checkbox"/> Test1	1 (1..255)	6 << TCP	192.168.1.100 to 192.168.1.125	500 to 1000	0.0.0.0 to 255.255.255.255	0 to 65535
<input type="checkbox"/>	1 (1..255)	6 << TCP	0.0.0.0 to 255.255.255.255	0 to 65535	0.0.0.0 to 255.255.255.255	0 to 65535
<input type="checkbox"/>	1 (1..255)	6 << TCP	0.0.0.0 to 255.255.255.255	0 to 65535	0.0.0.0 to 255.255.255.255	0 to 65535

## 3.7 Management

### 3.7.1 Status

This page shows the current status and some basic settings of the device, such as System information, Wireless Configuration, TCP/IP Configuration, and WAN Configuration.

## WLAN Access Point


Site contents:

- Setup Wizard
- Operation Mode
- Wireless
- TCP/IP Settings
- Firewall
- QoS
- Management
- Status
- Statistics
- DDNS
- Time Zone Setting
- Denial-of-Service
- Log
- Upgrade Firmware
- Save/Reload Setting
- Password
- Logout

### Access Point Status

This page shows the current status and some basic settings of the device.

System	
Uptime	0day:0h:19m:17s
Firmware Version	v1.2f-020409T
Build Time	Mon Feb 2 11:43:23 CST 2009
Wireless Configuration	
Mode	AP
Band	2.4 GHz (B+G+N)
SSID	RTL865x-GW
Channel Number	11
Encryption	Disabled
BSSID	00:e0:4c:86:51:01
Associated Clients	0
TCP/IP Configuration	
Attain IP Protocol	Fixed IP
IP Address	192.168.1.1
Subnet Mask	255.255.255.0
Default Gateway	192.168.1.1
DHCP Server	Enabled
MAC Address	00:e0:4c:86:51:01
WAN Configuration	
Attain IP Protocol	Fixed IP Disconnected
IP Address	0.0.0.0
Subnet Mask	0.0.0.0
Default Gateway	0.0.0.0
MAC Address	00:e0:4c:86:51:02



### 3.7.2 Statistics

This page shows the packet counters for transmission and reception regarding to wireless and Ethernet networks.

## WLAN Access Point

Site contents:

- Setup Wizard
- Operation Mode
- Wireless
- TCP/IP Settings
- Firewall
- QoS
- Management
- Status
- Statistics
- DDNS
- Time Zone Setting
- Denial-of-Service
- Log
- Upgrade Firmware
- Save/Reload Setting
- Password
- Logout

### Statistics

This page shows the packet counters for transmission and reception regarding to wireless and Ethernet networks.

<b>Wireless LAN</b>	<i>Sent Packets</i>	193
	<i>Received Packets</i>	117
<b>Ethernet LAN</b>	<i>Sent Packets</i>	473
	<i>Received Packets</i>	380
<b>Ethernet WAN</b>	<i>Sent Packets</i>	0
	<i>Received Packets</i>	0

### 3.7.3 DDNS

Dynamic DNS is a service that provides you with a valid, unchanging, internet domain name (an URL) to go with that (possibly ever-changing) IP address.

The screenshot shows the 'Dynamic DNS Setting' page in the WLAN Access Point configuration interface. The left sidebar contains a tree view with 'Management' expanded and 'DDNS' selected. The main content area has a blue header 'Dynamic DNS Setting' and a descriptive paragraph: 'Dynamic DNS is a service, that provides you with a valid, unchanging, internet domain name (an URL) to go with that (possibly everchanging) IP-address.' Below this is a checkbox for 'Enable DDNS' which is unchecked. The 'Service Provider' is set to 'DynDNS' in a dropdown menu. The 'Domain Name' is 'host.dyndns.org' in a text box. The 'User Name/Email' and 'Password/Key' fields are empty. A 'Note' section provides links for TZO and DynDNS accounts. At the bottom are 'Apply Change' and 'Reset' buttons.

### 3.7.4 Time Zone Setting

You can maintain the system time by synchronizing with a public time server over the Internet.

The screenshot shows the 'Time Zone Setting' page in the WLAN Access Point configuration interface. The left sidebar contains a tree view with 'Management' expanded and 'Time Zone Setting' selected. The main content area has a blue header 'Time Zone Setting' and a descriptive paragraph: 'You can maintain the system time by synchronizing with a public time server over the Internet.' Below this is the 'Current Time' displayed as 'Yr 2000 Mon 1 Day 1 Hr 0 Mn 20 Sec 48'. The 'Time Zone Select' dropdown is set to '(GMT+08:00)Taipei'. There are two checkboxes: 'Enable NTP client update' (unchecked) and 'Automatically Adjust Daylight Saving' (unchecked). The 'NTP server' dropdown is set to '192.5.41.41 - North America', with a '(Manual IP Setting)' option available. At the bottom are 'Apply Change', 'Reset', and 'Refresh' buttons.

### 3.7.5 Log

This page can be used to set remote log server and show the system log.

The screenshot shows the 'WLAN Access Point' configuration interface. On the left is a navigation tree with 'Management' expanded to show 'Log'. The main content area is titled 'System Log' and contains the following elements:

- Text: 'This page can be used to set remote log server and show the system log.'
- Form fields:
  - Enable Log**
  - system all**       **wireless**       **DoS**
  - Enable Remote Log**      **Log Server IP Address:**
- 
- Log output area (text area with scrollbar):

```
0day 00:22:37 00000000 (epc == 0040592c, ra == 00405908)
0day 00:22:37 br0: port 2(wlan0) entering disabled state
0day 00:22:37 br0: port 1(eth0) entering disabled state
0day 00:22:37 br0: port 2(wlan0) entering disabled state
0day 00:22:37 device wlan0 left promiscuous mode
0day 00:22:37 device wlan0 entered promiscuous mode
0day 00:22:37 br0: port 2(wlan0) entering listening state
0day 00:22:37 br0: port 1(eth0) entering listening state
0day 00:22:37 br0: port 2(wlan0) entering learning state
0day 00:22:37 br0: port 2(wlan0) entering forwarding state
0day 00:22:37 br0: topology change detected, propagating
0day 00:22:37 br0: port 1(eth0) entering learning state
0day 00:22:37 br0: port 1(eth0) entering forwarding state
0day 00:22:37 br0: topology change detected, propagating
```
- 

### 3.7.6 Upgrade Firmware


This page allows you upgrade the AP Router firmware to new version. **Please note DO NOT** power off the device during the upload because it may crash the system.

The screenshot shows the 'WLAN Access Point' configuration interface. On the left is a navigation tree with 'Management' expanded to show 'Upgrade Firmware'. The main content area is titled 'Upgrade Firmware' and contains the following elements:

- Text: 'This page allows you upgrade the Access Point firmware to new version. Please note, do not power off the device during the upload because it may crash the system.'
- Form fields:
  - Select File:**
-

### 3.7.7 Save/Reload Setting


This page allows you save current settings to a file or reload the settings from the file which was saved previously. Besides, you could reset the current configuration to factory default.



The screenshot shows the 'WLAN Access Point' web interface. On the left is a navigation tree with 'Management' selected, containing items like Status, Statistics, DDNS, Time Zone Setting, Denial-of-Service, Log, Upgrade Firmware, Save/Reload Setting, Password, and Logout. The main content area is titled 'Save/Reload Settings' and includes a descriptive paragraph: 'This page allows you save current settings to a file or reload the settings from the file which was saved previously. Besides, you could reset the current configuration to factory default.' Below this are three sections: 'Save Settings to File:' with a 'Save...' button; 'Load Settings from File:' with a text input field, a '瀏覽...' (Browse) button, and an 'Upload' button; and 'Reset Settings to Default:' with a 'Reset' button.

### 3.7.8 Password


This page is used to set the account to access the web server of AP Router. Empty user name and password will disable the protection.




The screenshot shows the 'WLAN Access Point' web interface. On the left is a navigation tree with 'Management' selected, containing items like Status, Statistics, DDNS, Time Zone Setting, Denial-of-Service, Log, Upgrade Firmware, Save/Reload Setting, Password, and Logout. The main content area is titled 'Password Setup' and includes a descriptive paragraph: 'This page is used to set the account to access the web server of Access Point. Empty user name and password will disable the protection.' Below this are three input fields: 'User Name:', 'New Password:', and 'Confirmed Password:'. At the bottom are two buttons: 'Apply Changes' and 'Reset'.

### 3.8 Logout

This page is used to logout WLAN AP Webserver.



Click "**Apply Change**" button to logout the webserver. And then, you will see the below screen:



## 4. Troubleshooting

This chapter covers some common problems that user may encounter while accessing the wireless router and some possible solutions for them. If you follow the suggested instructions to configure the wireless router, but router still does not function properly, please contact your local dealer for assistance.

### Q1) **Can not connect to the wireless router.**

Ans: Check the following.

- a) If the wireless router is properly installed, if LAN connections are OK, and if wireless Router is powered on.
- b) Ensure that your PC and wireless router are on the same network segment.
- c) If your PC is set to "Obtain an IP Address automatically" (DHCP client), restart it.
- d) If your PC uses a Fixed (Static) IP address, ensure that it is using an IP Address within the range **192.168.1.2** to **192.168.1.254** and thus compatible with the wireless router's default IP Address of **192.168.1.1**. Also, the Network Mask should be set to **255.255.255.0** to match the wireless router. In Windows, you can check these settings by using "**Control Panel → Network**" to check the "**Properties**" for the TCP/IP protocol.

### Q2) **When I enter a URL or IP address I get a timed out error.**

Ans: A number of things could be causing this. Try the following troubleshooting steps.

- a) Check if other PCs work. If they do, ensure that your PCs IP settings are correct. If using a fixed (static) IP address, check the Network Mask, Default gateway, and DNS as well as the IP Address.
- b) If the PCs are configured correctly, but still not working, check the wireless router. Ensure that it is connected and on. Connect to it and check its settings. If you can't connect to it, check the LAN and power connections.
- c) If the wireless router is configured correctly, check your Internet connection (DSL/cable modem etc) to see that it is working correctly.

### Q3) **Some applications do not run properly when using the wireless router.**

Ans: The wireless router processes the data passing through it, so it is not transparent.

Use the Special Applications feature to allow the use of Internet applications that do not function correctly. For example, you can use DMZ function, this should work with almost every application but there is a security risk since firewall is disabled and only one PC can be used in this feature.

**Q4) My PC can not locate the wireless router.**

Ans: Check the following.

- a) If your PC is set to Infrastructure Mode, because the router is always in Infrastructure Mode.
- b) If the SSID on your PC and wireless router are the same. Remember that the SSID is case-sensitive.
- c) If both of your PC and wireless router have the same WEP settings. The default setting for the wireless router is disabled, so your wireless station should also have WEP disabled.
- d) If WEP is enabled on the wireless router, your PC must have WEP enabled, and the key tables (64/128 bit encryption) must match.
- e) If the wireless router's wireless screen is set to allow LAN access to select wireless stations only, then each of your wireless stations must have been selected or access will be blocked.
- f) To see if radio interference is causing a problem, check if connection is possible when close to the wireless router. Remember that the transmission range can be as short as 100 feet in poor environment.

**Q5) Wireless connection speed is very slow.**

Ans: A wireless system transmission speed depends on the distance and the environment.

To obtain the highest possible connection speed, you can try the followings:

- a) Try to adjust wireless router location and orientation.
- b) If there are interference problems, change to another wireless channel.
- c) If other devices cause the interference, you should turn off that device or relocate it.

**Q6) The "Status" light is ON (steady Green) after power on, it means the router is hung**

Ans : Please disconnect the power adapter from the power jack on the router and reconnect the power adapter again to the router, check if the "Status" light is flashing normally.